



**DISPLAYS2GO**  
CONNECTING PEOPLE & BRANDS WITH THE WORLD

**DISPLAYS2GO DIGITAL**

# **32" Digital Signage Mirror**

## **USER MANUAL**



Model: DGMM32  
Description: 32-inch Digital Signage Mirror  
V1.2

NOTE: Before using the product, please read the instructions carefully.

Do not attempt to disassemble this product. If the product does not work properly, please call our Customer Service Department at 1-844-221-3393.

## Contents

<b>Features</b> .....	<b>3</b>
<b>Safety Warnings and Precautions</b> .....	<b>3</b>
<b>Assembly and Connection</b> .....	<b>6</b>
Packing List .....	6
Interfaces .....	7
<b>Mouse</b> .....	<b>8</b>
<b>Description of Basic Operation</b> .....	<b>9</b>
Power on/Standby.....	9
About Launch Desktop.....	9
Description of Wallpaper Switch.....	9
File Explorer.....	10
Local Settings.....	10
Status of Menu bar .....	11
<b>DiViEx APP Introduction</b> .....	<b>12</b>
System requirements .....	12
How to upload media files .....	12
Settings.....	14
Edit picture .....	14
Music .....	16
Factory Reset .....	16
Screen Rotate .....	17
Hide Navigation Bar .....	17
Choose System Language.....	18
<b>Technical Specifications</b> .....	<b>19</b>
<b>Troubleshooting</b> .....	<b>21</b>
<b>Cleaning and Maintenance</b> .....	<b>23</b>
<b>Names and Contents of Toxic and Hazardous Substances or Elements in the Product</b> .....	<b>24</b>



## Features

1. Display shrinks to a small version when people come close to the signage;
2. Supports Wi-Fi;
3. Self-recovery from system crashes, can be left for 24/7 hours unattended;
4. Android system can carry out product customization development;
5. Support for two videos to play simultaneously;
6. IP 43 rating;
7. Can convert to the stand-alone version;
8. Multi-screen synchronization: the same content on multiple screens, the same playback progress;
9. Supports USB plug-in update program.





## Safety Warnings and Precautions

Thank you for buying this product from Displays2go. We have taken personal safety into account in product design and carried out rigorous tests in the factory. However, improper installation and use can lead to electric shock and fire. To ensure safe use, maximize the performance of the product, and prolong the service life of the product, please read and follow all instructions carefully before using the product.

**Keep instructions for future reference.**

We strongly recommend using standard adapters and portable power supplies, or adapters with internal circuit breakers, to prevent bad power supplies from damaging the device.

### Symbol Legends:


-  **Warning: May cause personal injury or death**
-  **The operation is prohibited**
-  **Caution: May cause damage or property loss**
-  **The operation must be executed**

### If any of the following occurs:

- Power outage or instable voltage.
- Abnormal sound or smell from the unit.
- AC power cord is damaged.
- Digital Signage is damaged due to drop, knock or impact.
- Any liquid or foreign matters fall into the enclosure.



**Turn off the Digital Signage immediately, pull out the plug from the power outlet, and ask the authorized personnel for maintenance immediately.**

 **If coal gas or other flammable gas leaks, do not pull out the plug of the LCD Digital Signage or other electrical appliances; instead, turn off the gas valve immediately, and open the doors and windows quickly.**



## WARNING



- Do not use power supply other than AC 110V, 60Hz.
- Cut off the power supply before connecting or disconnecting any cables.
- Do not place the Digital Signage on any instable positions, or else it may be damaged or cause fire.
- Do not place the Digital Signage in the positions such as:
  1. The environment subject to direct strong sunlight, moisture, extreme temperature or too much dust;
  2. The environment with flammable or explosive materials;
  3. The environment with flammable or corrosive gases;
- Do not use damaged or inappropriate power outlets, and ensure that the plugs and outlets contact properly.
- Do not let dust or metal deposits adhere to the plugs and outlets.
- Do not damage the power cords:
  1. Do not modify the power cords;
  2. Do not place heavy objects on the power cords;
  3. Keep the power cords away from heat source;
  4. Do not pull the cord to remove the plug.
- Do not connect too many plugs to one outlet in parallel, or else it may cause fire due to excessive power consumption.
- Do not approach the Digital Signage with open flame (e.g. a lighted candle), or else it may cause electric shock or fire.
- Do not put any sharp objects, metal or liquid into the vents or let them touch the signal terminals to avoid short circuit, product damage, and electric shock.
- The openings in the enclosure are designed for ventilation and cooling, to ensure long time reliable running of components inside the enclosure and prevent overheating. Do not block the openings when place the unit.



Do not touch the plugs with wet fingers, or else it will cause electric shock.

Do not use the Digital Signage in stormy weather, especially when there is lightning; instead, please disconnect the power and antenna plugs to avoid lightning strike.



Do not disassemble the Digital Signage without permission, or else it may cause electric shock or fire. Please ask qualified technician for repair.



## CAUTION

- Do not let children climb onto the Digital Signage.
- Keep the small parts away from children to prevent them from swallowing.
- If the Digital Signage won't be used for a long time, please turn it off and pull out the power plug.
- To adjust the position of the Digital Signage, please disconnect all power cords and move slowly to avoid tip over.
- Do not scratch or knock the LCD with hard object, or twist and squeeze the LCD.
- Do not turn on the unit immediately when it is moved from a place with low temperature to high temperature, or else it will cause condensation and malfunction.
- Before cleaning the Digital Signage, please pull out the power plug; wipe with soft cloth; do not use industrial chemicals; prevent foreign matters from entering the machine. Improper cleaning (such as cleaning solution, water) may damage the product, erase the printed information, and even cause damage of the components if fluid flows in, resulting in machine failure.
- If the unit displays the same screen for a long time or the moving picture has fixed text or icon, it will leave ghosting on the screen and won't disappear when the unit is turned off; it is normal and isn't covered by the warranty.
- The power of the Digital Signage can be cut off by pulling out the plug.
- If the LCD screen ruptures and the liquid splashes on the skin, please rinse for 15 minutes with clean water immediately, and consult your doctor.
- To carry the Digital Signage with hands, please grab and hold the edges; do not apply pressure on the panel.
- Use the Digital Signage properly: Use in proper lighting conditions; insufficient lighting or long time watching will impair your eyesight.
- When the plug or coupler is used as disconnection device, it should be easy to operate the device.
- Insert the plug into the outlet properly, or else it may cause sparks and fire.
- The technical specifications printed herein and on the packaging are subject to change without prior notice. The Manual may be slightly different from actual operation, and the latter is applicable.

## Assembly and Connection

### Packing List


Name	QTY
Digital Signage	1
Power cord	1
Remote	1
Antenna	1

Name	QTY
Operation Manual	1
Wall-Mount Bracket	1
Wood Screws with Plastic Washers	4
Masonry Anchors and Bolts	4

Note:

Contact local dealer if you have questions about the operation, debugging and connection of the unit; if the unit doesn't work normally, please cut off the power immediately and consult the dealer. The unit is class-A product, which may cause radio interference in living environment. In this case, please take feasible measures, and use power plug as the disconnection device.


## Interfaces



1. DC 12V 2. RJ45 3. USB 4. USB 5. HDMI OUT 6. TF card 7. 3.5MM  
EARPHONE; 8. POWER SWITCH 9. POWER PLUG SOCKET

Note: Please pull out the power plug before installing or disassembling the unit!

Scan QR code to visit the product page:



## Remote Control

### Installing batteries for the remote control:

Remove the battery cover and insert two AAA batteries (1.5V).

Ensure that the battery polarity matches the "+" / "-" marks in the battery compartment of the remote control.

### Precautions for using the remote control:

- Aim the remote control at the receiver window. Do not place any object between the remote control and the receiver window to avoid interference with the normal operation.
- Keep the remote control away from violent vibration. In addition, do not set or place the remote control in direct sunlight, or else the remote control may be deformed by heat.
- The remote control may be invalid when the receiver window of the unit is in direct sunlight or strong lighting; in this case, please adjust the angle of the lighting or the unit or approach the receiver window to use it.
- The distance of remote control will be shortened if the battery voltage is insufficient; in this case, please replace with new batteries; if the remote control won't be used for a long time or the batteries are run out, please take out the batteries to avoid corrosion due to battery leakage, which will damage the remote control.
- Do not use batteries of different types or mix new batteries with old ones. Always replace the batteries in pairs.
- Do not put the batteries in fire, or charge or disassemble them, or charge, short circuit, disassemble, heat or burn used batteries. Please dispose of waste batteries in accordance with local environmental regulations. Do not expose the batteries in overheated environments such as sunlight and fire.

### Description of remote control buttons:



Button	Function
	Power switch
	Setting
	Mute
	Turn up the volume
	Turn down the volume
	Turn on/off "MAGIC MODE"
	Play or pause
	Stop
	Last
	Next
	Confirm selection
	To move the cursor up
	To move the cursor down
	To move the cursor left
	To move the cursor right
	Menu
	Home button
	Go back to the parent menu
	Mouse mode
	Delete

**NOTE:** Press the button to turn on the "MAGIC MODE", the ad will shrink to the top left corner when you come close to the magic mirror signage. Press the button again to turn off the "MAGIC MODE" the ad will always be full of screen whether you come close or away from the magic mirror signage.












## Description of Basic Operation


### Power on/Standby

Insert the power plug into the outlet. If the Digital Signage has the switch button “I”, turn it on; if you press the switch button “O”, the Digital Signage enters standby state.

### About Launch Desktop

#### Description of Desktop Icons

Icon	Function
	Home page
	Back
	Background applications
	Sound -
	Sound +
	Screenshot
	Main applications
	File Manager
	Settings
	Browser
	Back to homepage



### Description of Wallpaper Switch

We suggest using a mouse to change the wallpaper.

Connect a mouse with the digital panel through USB port, then follow the steps below:

1. click “Setting”
2. At the setting menu, click “Display”
3. At the Display setting menu, click “Gallery”, or “Wallpaper”
4. Then select an image you would like to set up as background.
5. Confirm the selection by clicking “Set wallpaper”.

## File Explorer

1. Click and enter the “File Manager” icon in the homepage (Fig. 1);
2. Click options in the “File Explorer” menu to read the files from different devices.




Fig.1




Fig.2

## Local Settings

1. Click the Settings icon in the Home page (Fig. 1) to enter “Wi-Fi” menu (Fig. 2);
2. Click options in the “Wi-Fi” menu and set up different options. (Fig. 3)




Fig.1




Fig.2




























Fig.3

## Description of Settings Interface (shown on the right)

Icon	Function
	WIFI switch
	Bluetooth
	More
	Display
	Notifications
	Home
	Sound
	USB
	Apps
	Screenshot Setting
	Storage
	Memory
	Location
	Security
	Accounts
	Google
	Languages & input
	Backup & reset
	Date & time
	Accessibility
	Developer options
	About device
	Other setting





## DiViEx APP Introduction


### System requirements:

Step 1: Before using this application, make sure your machine meets or exceeds the following system requirements:

CPU	RK3288
RAM	2GB
Operating system	Android 7.1

### How to upload media files:

Step 2: Make new directory named "MediaFolder" in root directory in U disk.



(F:) >			
^	Name	Dete modified	Type
	MediaFolder	2020/3/13 16:46	File folder

Open "MediaFolder", create 3 subfolders, and change their names to "Images", "Videos", "Music".  
Copy the media file to be displayed, image to "Images", video to "Videos", Music to "Music"



(F:) > MediaFolder >			
^	Name	Dete modified	Type
	Images	2020/3/13 16:48	File folder
	Music	2020/3/13 16:51	File folder
	Videos	2020/3/13 16:51	File folder

Format requirement:

Image	JPG/JPEG/BMP/PNG
Video	MPEG1/MPEG2/MPEG4/H.264/H.265/WMV/MKV/TS/flv
Music	AAC/MP3/AMR/OGG/PCM

Step 3: Click and enter the “File Manager” icon in the homepage (Fig. 1). Plug in the USB drive into the device and copy the MediaFolder in the USB drive and paste it into the internal flash, check if it was done successfully, then pull out the USB drive.




Fig.1




Fig.2




Fig.3




Fig.4




Fig.5




Fig.6

Step 4: Click and enter the “File Manager” icon in the homepage (Fig. 1). Then Click the DiViEx App to open it, and click the “PLAY” to start playing the media content.




Fig.1




Fig.2




Fig.3




Fig.4

### Settings:


Step 1: Select the time you would like each picture to be on the screen for by dragging the bar to the desired time. Select how you would like the images to display. Select the desired transition effect between pictures.


- **Auto Boot**  
If enable, application will auto boot when android system boot
- **Auto Play**  
If enable, application will show all resource including images、videos
- **Choose Picture display mode**  
"Adapt", "Center", "Reshaped by the original size", "Set Image center adaptation display"
- **Set Picture switch mode**  
During the image conversion process, there are 10 animations: "Normal", "Depth", "Zoom", "CubeIn", "ForegroundToBackground", "Flip3D", "FlipHorizontal", "RotateDown", "Accordion, Stack".



### Edit picture:


All pictures will be shown on the left. Pick the one you would like to make changes.

- **Edit picture**  
Drag the corner and edge handles around the image to specify the boundaries of your picture.
- **Filter**  
Set different filter for the picture, we support the following filter: AUTO\_FIX, BLACK\_WHITE, BRIGHTNESS, CONTRAST, CROSS\_PROCESS, DOCUMENTARY, DUE\_TONE, FILL\_LIGHT, FISH\_EYE, FLIP\_HORIZONTAL, FILP\_VERTICAL, GRAIN, GRAY\_SCALE, LOMISH, NEGATIVE, PSTERIZE, ROTATE, SATURATE, SEPIA, SHARPEN, TEMPERATURE, TINT, VIGNETTE.
- **Reset**  
Revert to the original image.
- **Download**    
It will save as a new picture when you click download button at the right corner.



- **Image deletion**


Click "✕" to delete unwanted pictures




## Music:

List all music files into Playlist library

- Add music to playing list music from Playlist library, you can click right arrow, music title will show the number of playlist music.



- To remove background music from the playlist, click the left arrow in the playlist



## Factory Reset:

1. Get into Settings, then click "Backup & reset" (Fig. 1)
2. Click "Factory data reset" (Fig. 2)
3. Choose "Erase SD card", then click "RESET DEVICE" to get the unit to Factory Reset (Fig. 3)




Fig. 1

Fig. 2

Fig. 3



### Screen Rotate:

1. Click the “Settings” icon in the home page (Fig. 1) and enter “Display” menu (Fig. 2);
2. Click options in the “Main screen rotation angle” menu and set up different options. After the restart, the screen will be rotated (Fig. 3)




Fig. 1




Fig. 2




Fig. 3

### Hide Navigation Bar:

1. Click the “Settings” icon in the home page (Fig. 1) and enter “Display” menu (Fig. 2);
2. Click “Hide Navigation Bar”. (Fig. 2)




Fig. 1




Fig. 2

**Choose System Language:**

1. Get into Settings, then click “Language & input” (Fig. 1)
2. Click “Languages”. (Fig. 2)
3. Then you can set up different language options. (Fig. 3)




Fig. 1

Fig. 2

Fig.3





## Technical Specifications

	ITEM	SPECIFICATION
Panel	LCD size	32"
	Light source	LED backlight
	Resolution	1920*1080 (pixels)
	Brightness (typ.)/(min)	≥300cd/m <sup>2</sup> (typ.)
	Contrast (typ.)	2000:1 (typ.)
	Response (ms)	8ms (typ.)
	Refresh rate	60Hz
	Viewing angle	178° (H)/178° (V)
	Color saturation	72%
	Viewable area	698.7mm (H) × 393.1mm (V)
	Chromaticness	262K
Power supply	Voltage	100V~240V, 50-60Hz
	Power Consumption	≤50W
Environment	Operating temperature (°C)	0~40°C
	Storage temperature (°C)	-10~60°C
	Storage humidity	10~60% RH Non-condensing
	Operating humidity	20~80% RH Non-condensing
	Maximum operating time (hrs/day)	24 hours
Functions	Operating system	Android 7.1
	Processor	RK3288, quad-core
	RAM	2G
	Built-in memory	16G
	Decoding resolution	1080P FHD compatible
	Playback mode	Support loop, inter-cut, timer, shim, etc.
	Touch support	NA

Functions	Supported Video Files	AVI, MPEG4, WMV, MKV, FLV, MP4, MOV
	Supported Photo Files	JPG, JPEG, BMP, PNG, GIF
	Audio output, supported files	Left and right audio channel, MP3
	RTC (real-time clock)	Yes
	Schedule power on/off	Yes
	System update	USB compatible
	App installation	Support download and installation
I/O interfaces	TF	*1
	Ethernet (RJ45)	*1
	HDMI	OUT *1
	VGA	N/A
	Headset	N/A
	USB	2
	SIM	N/A
Structure	IP	IP 43(Front panel)
	Net weight	14kg
	Gross weight	17kg
	Unit dimensions (W*D*H)	798*65*490mm
	Package dimensions (W*D*H)	905mm*140 *610mm
	Shell material	aluminium alloy/sheet metal
	Shell color	Silver+black
Language	OSD	English/Simplified Chinese

## Troubleshooting the Digital Signs – DGMM32

Issue	Probable Cause	Solutions
● No picture or sound	<ul style="list-style-type: none"> <li>➤ Unit not plugged into wall outlet</li> <li>➤ Power cord not properly connected to the terminal on the back of the unit.</li> <li>➤ Unit not powered on</li> <li>➤ Wall outlet not working</li> </ul>	<ul style="list-style-type: none"> <li>□ Check that the unit is plugged into wall outlet.</li> <li>□ Confirm that the power cord is connected to the terminal on the back of the unit.</li> <li>□ Turn the on/off toggle switch located on the back of the unit, lower center, to the “on” position.</li> <li>□ Unplug unit, wait 20 seconds, plug unit back into outlet and try again.</li> <li>□ Make sure that outlet is working by plugging in a different electrical device.</li> <li>❖ <b>If all of the above have been checked and the issue is not resolved, contact a customer service representative.</b></li> </ul>
● No sound (but picture is working)	<ul style="list-style-type: none"> <li>➤ Content/Video does not have sound.</li> <li>➤ Content format is not compatible.</li> <li>➤ Speakers do not work.</li> </ul>	<ul style="list-style-type: none"> <li>□ Confirm content is one of the following compatible formats: AVI, MPEG4, WMV, MKV, flv, MP3, MP4, MOV.</li> <li>□ If unit is connected to Wi-Fi, go to YouTube and play video that has sound</li> <li>□ Unplug unit, wait 20 seconds, plug unit back into outlet and try again.</li> <li>□ Try playing the content on a different device (smart phone, computer or tablet)</li> <li>❖ <b>If all of the above have been checked and the issue is not resolved, contact a customer service representative.</b></li> </ul>
● No picture (but sound is working)	<ul style="list-style-type: none"> <li>➤ Content file damaged.</li> <li>➤ Content format is not compatible.</li> <li>➤ Screen damaged or defective.</li> </ul>	<ul style="list-style-type: none"> <li>□ Confirm content is one of the following compatible formats: AVI, MPEG4, WMV, MKV, flv, MP3, MP4, MOV.</li> <li>□ Try playing the content on a different device (smart phone, computer or tablet)</li> <li>□ Unplug unit, wait 20 seconds, plug unit back into outlet and try again.</li> <li>❖ <b>If all of the above have been checked and the issue is not resolved, contact a customer service representative.</b></li> </ul>
● Remote not working	<ul style="list-style-type: none"> <li>➤ Batteries not inserted properly.</li> <li>➤ Batteries are dead.</li> <li>➤ Standing too far from the unit.</li> </ul>	<ul style="list-style-type: none"> <li>□ Check that battery is inserted properly with positive and negative orientation.</li> <li>□ Insert new batteries.</li> <li>□ Stand within 1 foot of the front of the unit and point the remote directly at the sensor.</li> <li>❖ <b>If all of the above have been checked and the issue is not resolved, contact a customer service representative.</b></li> </ul>

<ul style="list-style-type: none"> <li>● No Wi-Fi signal</li> </ul>	<ul style="list-style-type: none"> <li>➤ Wi-Fi is not turned on in product settings.</li> <li>➤ Wi-Fi is not connected to a network</li> <li>➤ Low or no signal from the router</li> <li>➤ Antenna is missing or not pointed upward.</li> <li>➤ Damaged PC board</li> </ul>	<ul style="list-style-type: none"> <li>□ Check that Wi-Fi is turned on in settings <ul style="list-style-type: none"> <li>○ Click the settings icon from the Android home screen. </li> <li>○ Click "Wi-Fi".</li> <li>○ Click the on/off icon in the upper right hand corner to turn on Wi-Fi. </li> <li>○ "On" will appear on the upper left hand side.</li> <li>○ Then select your Wi-Fi network</li> </ul> </li> <li>□ Confirm that the antenna is in place and pointed upward.</li> <li>□ Check that other devices are receiving the signal. <ul style="list-style-type: none"> <li>○ <b>If other devices are not receiving the Wi-Fi signal, please contact your internet service provider.</b></li> </ul> </li> <li>□ Unplug or reset the router and wait for 20 seconds. Restart the router and check.</li> <li>❖ <b>If all of the above have been checked and the issue is not resolved, contact a customer service representative.</b></li> </ul>
<ul style="list-style-type: none"> <li>● Parts missing or Damaged</li> </ul>	<ul style="list-style-type: none"> <li>➤ Parts missed during manufacturing. (No charge for replacements)</li> <li>➤ Parts lost or damaged by the customer. (There is charge for replacements)</li> </ul>	<ul style="list-style-type: none"> <li>❖ <b>Contact a customer service representative.</b></li> </ul>
<ul style="list-style-type: none"> <li>● Having problems with installing software or getting content to play</li> </ul>	<ul style="list-style-type: none"> <li>➤ Did you purchase the DisplayIt!Xpress software from Displays2go?</li> <li>➤ Did the customer purchase or downloaded another 3<sup>rd</sup> party software onto the product?</li> </ul>	<ul style="list-style-type: none"> <li>□ If you purchased DisplayIt!Xpress software from Displays2go or from Best Wave directly, please contact Best Wave at <b>support@bestwave.com or (480)368-8900 ext. 2</b></li> <li>□ If you purchased or downloaded another 3<sup>rd</sup> party software onto the product, please contact the 3<sup>rd</sup> party software company's customer support for assistance.</li> </ul>
<ul style="list-style-type: none"> <li>● Cannot upload content</li> </ul>	<ul style="list-style-type: none"> <li>➤ Content format is not compatible.</li> <li>➤ Content files are too large.</li> <li>➤ Port being used is defective</li> <li>➤ App being used to play content is defective.</li> <li>➤ Android board is defective.</li> </ul>	<ul style="list-style-type: none"> <li>Y Confirm content is one of the following compatible formats: AVI, MPEG4, WMV, MKV, flv, MP3, MP4, MOV.</li> <li>Y Confirm file size is less than available space.</li> <li>❖ <b>If all of the above have been checked and the issue is not resolved, contact a customer service representative.</b></li> </ul>
<ul style="list-style-type: none"> <li>● Issues using pre-installed apps</li> </ul>	<ul style="list-style-type: none"> <li>➤ Mistake in storing content to NAND Flash (shown on pg. 11)</li> </ul>	<ul style="list-style-type: none"> <li>Y DiViEx App steps Explorer &gt; Select USB &gt; Select Multi &gt; highlight files &gt; Editor &gt; Select</li> </ul>

	<ul style="list-style-type: none"> <li>➤ App is defective</li> <li>➤ Android board is defective.</li> </ul>	<p>Copy &gt; Home &gt; NAND &gt; MediaFolder &gt; Images&gt; Editor &gt; Paste</p> <ul style="list-style-type: none"> <li>○ Open DiViEx app and select desired transitions, slide time and looping &gt; Play</li> </ul> <p>Y MX Player steps &gt; Follow same steps as DiViEx App &gt; MediaFolder &gt; Video &gt; Editor &gt; Paste.</p> <ul style="list-style-type: none"> <li>○ Open MX Player and select video to play.</li> <li>○ Loop video: While the video is playing, click on the video and there should be 3 dots in the top right corner. Click on the 3 dots &gt; play &gt; check desired Loop option</li> </ul> <p>Y <b>If all of the above have been checked and the issue is not resolved, contact a customer service representative.</b></p>
--	---	---

If all of the potential solutions have been tested for a particular issue and problems have not been resolved, contact a customer service representative for guidance.

Contact Information:  
Website: [www.displays2go.com](http://www.displays2go.com)  
Phone: 844-221-3388

## Cleaning and Maintenance

1. Avoid strong vibration or impact on the product.
2. Keep the product dry to avoid possible damage by moisture.
3. Don't place the product under direct sunlight which may shorten the service life of the screen.
4. Clean screen and product by using a glass cleaner.
5. If the product will not be used for a long time, pull out the power cord to prevent the internal short circuit or other potential dangers.

## Names and Contents of Toxic and Hazardous Substances or Elements in the Product

Part name	Toxic and hazardous substances or elements					
	Pb	Hg	Cd	Cr <sup>6+</sup>	PBB	PBDE
Display		○	○	○	○	○
Shell	○	○	○	○	×	×
Circuit board assembly *		○	○	○	○	○
Wires	○	○	○	○	○	○
Metal parts	○	○	○	○	○	○
Packaging materials*	○	○	○	○	○	○
Remote		○	○	○	○	○
Speaker		○	○	○	○	○
Accessories*	○	○	○	○	○	○

\* : Circuit board assembly includes PCB and the electronic elements thereof;

Packaging materials include packaging box, styrofoam, etc.;

Other accessories include instruction manual.

○ : the content of the toxic and hazardous substances or elements in the part is lower than the limit specified in GB/T 26572-2011 standard.

× : the content of the toxic and hazardous substances or elements in the part is higher than the limit specified in GB/T 26572-2011 standard.

The table shows that the machine contains harmful substances inside. The data is provided by material suppliers and verified by the company according to the material type. Some materials contain harmful substances that can't be replaced in present technology. We are dedicated to improving this.

The EFUP of the product is ten years. The pollution control label is shown on the right. 

The EFUP is valid only when the user operates in the normal conditions specified in the manual herein.

### **Waste Electrical and Electronic Products Recycling and Disposal Regulations**

To protect the earth, if you do not need this product or its service life expires, please abide by your local **Waste Electrical and Electronic Products Recycling and Disposal Regulations** or send it to qualified local manufacture for recycling.

This Manual is for reference only and is subject to change without prior notice.