



Retail Cabinet With Sliding Doors And Adjustable Shelf - Assembly Instructions

SKU: MRCHV4WHKD (48" Display Counter, White)

SKU: MRCHV4BKKD (48" Display Counter, Black)

SKU: MRCHV5WHKD (58" Display Counter, White)

SKU: MRCHV5BKKD (58" Display Counter, Black)

SKU: MRCHV6BKKD (70" Display Counter, Black)



 **DISPLAYS2GO**

Display Stuff Better.

TOOLS NEEDED



Scan the QR code to visit the product page and watch our assembly video.



NOTE: It is recommended that two persons assemble this unit.

1.

BASE ASSEMBLE

BOTTOM PANEL (x1)

TOE KICK (x1)

#10 CAM LOCK (x22)

BOLT (x6)

GLID (x4)

FRONT PANEL (x1)

FALSE BOTTOM (x1)

1. Connect toe kick with bottom panel using bolts.
2. Insert and tighten #10 cam lock.
3. Attach glides to the toe kick.
4. Connect front panel with bottom using bolts.
5. Insert and tighten #10 cam lock.
6. Attach glides to front panel.
7. Connect false bottom with front panel using bolts.
8. Insert and tighten #10 cam locks.



2.

SIDE PANEL AND FRONT GLASS ASSEMBLE

LEFT SIDE PANEL (x1)

RIGHT SIDE PANEL (x1)

BOLT (x12)

FRONT GLASS (x1)

1. Attach assembled base to right side panel; tighten.
2. Insert front glass.
3. Attach left side panel to assembled base; tighten.
4. Sit showcase on floor.



3.

ALUMINUM EXTRUSION RAIL ASSEMBLE

U CHANNEL (x6FT) **#6 x 158 PHILLIPS SCREW** (x6)
AK0312 (x1) **FELT** (x12FT)
AK0313 (x1) **#12 SCREW CAP** (x6)
AK0314 (x1)

1. Attach U channel to top glass, cut off leftover.
2. Attach AK0312 to top glass; tighten by using 2 #6 x 158 phillips screw.
3. Tighten AK0314 with case by using 4 #6 x 158 phillips screw.
4. Put AK0313 onto bottom panel.
5. Adhere felt on both AK0312 and AK0314.
6. Place #12 screw caps onto #6 x 158 phillips screws.



4.

STANDARD ASSEMBLE

SS17CD (x3)
#6 x 34 PHILLIPS SCREW (x3)
#6 x 12 PAN SCREW (x6)

1. Tighten SS17CD to AK0314 with 1 #6 x 34 phillips screw.
2. Tighten the same SS17CD on base with 2 #6 x 12 pan screws.
3. Repeat steps 1 & 2 to assemble the other 2 pcs of SS17CD.



5.

GLASS SHELF & TOP GLASS ASSEMBLE

BT10C (x3)

10" SHELF GLASS (x1)

TOP GLASS (x1)

1. Place BT10C on SS17CD with proper height.

2. Place 10" glass shelf on BT10C.

3. Gently sit top glass onto the top frame.



6.

DOOR PANEL ASSEMBLE

DOOR PANEL (x2)

1. Insert doors on showcase.

