

DISPLAYS2GO

MODEL #: CGEB01WH  
CGEB01BK

User manual

True Wireless Bluetooth Headsets  
Each Headset can be used separately

Congratulations, and thank you for choosing CGEB01WH/BK headsets. This manual will help you operate the headsets. Please first familiarize yourself with the bluetooth functionality of your mobile phone or other devices before using the headsets. Enjoy your time with our product.

**Safety rules:**

- Please follow the rules described in this manual closely to ensure your safety. Before using this headset, we would strongly encourage you to read through this user manual carefully.
- Be more wary of any edges, uneven surfaces, metal parts accessories and its packaging so as to prevent any possible injury or damage.
- Do not modify, repair or dismantle this headset. It may result in fires, electric shocks, complete breakdown of this product. All of which, are not covered under warranty.
- Do not use any diluents or volatile liquid to clean the headset.
- Do not use product, in a hazardous location.

**Accessories**

Headsets  
Left Right  
Large  
Medium  
Small  
Ear Tips

Charging box

USB charging cable

User manual

**Graphical Representation**

- Master earphone(L)
- Slaver earphone(R)
- Charging box Button
- Charging box LED indicator
- Charging box
- USB input
- Multifunction Touch button
- Microphone and LED indicator

**FIT**

In order to get best audio performance, try every eartips (small, medium and large), the correct seal in your ear to achieve optimal fit and stability.

In order to get better signal distance, please wear headset as below pictures showed, multifunction button round end towards to mouth direction.

**Charging**

The bluetooth headsets and charging box must be fully charged before first time use.

**1 Charge the bluetooth headsets**

Magnetic contact recharging, the LED indicator will turn red when charging, and will turn off when the earbuds are fully charged.

Note:  
1. When you are playing the music, blue LED light will flash slowly.  
2. The red light will flash when the battery is low.

**2 Charge the charging box**

Use the USB cable to connect the adapter or computer USB socket to charge the charging box

**Single headset operation**

**1 Power on/ Power off**

Pick up the headsets from charging box, the two earbuds will start pairing each other automatically. After above pair finished, Earbuds go pairing with smartphones within a certain distance.

**Power on:** Long press the Multifunction button for about 4 seconds, the indicator light will flash blue.  
**Power off:** Long press the Multifunction button for about 4 seconds, the indicator light will flash red.

**2 Pairing : first time to use**

In power off status, long press the multifunction button for 6 seconds, the indicator lights will flash red and blue alternately. then turn on your cellphone bluetooth, search "CGEB01WH/BK" and click connecting, if ask for passkey, pls enter "0000".

**Stereo headsets operation**

**1 Power on**

Long press the Multifunction button for about 4 seconds, the indicator light will flash blue and a warning tone will be heard.

**2 Power off: power off one headset only**

Press and hold the Multifunction button for 4 seconds the LED will flash red and a notification sound will be heard accordingly. Only need to power off one headset, the other one will power off automatically if two headsets connected.

**3 Pairing: first time use**

1. In power off status, press and hold the Multifunction buttons of two headsets at the same time for 6 seconds, the red and blue LEDs will flash alternately, put two headsets closely and you can find two "CGEB01WH/BK" in your phone. Please do not click any one of them to pair.

2. Two headsets will pair to each other automatically. Master headset(L) flashes blue and red light alternately quickly. Slaver headset (R) flashes blue light slowly, you can see only one "BT-03" in your phone.

**4 Search and connection**

When master headset flashes red and blue alternately, Please wait several seconds until only one "CGEB01WH/BK" shows in your phone then click to connect, input the code "0000" if needed.

Notice:  
Please do not click "CGEB01WH/BK" to connect before two headsets connected to each other. Otherwise the stereo function is not available.

**5 Pairing successful**

Master headset LED flash blue slowly and slaver headset flash blue two times, only one "CGEB01WH/BK" show in your phone it means connection succeed. (For previous paired headset and cellphone it will connect automatically after you power on)

**6 Calling**

**Answer call/End call:** While talking, Single touch to hang up, Double touch to reject, Single touch to end a call.  
**Reject call:** Double Touch the control button to reject the incoming call. Double Touch the control button to redial the last number you called on your phone. (Only L headset) Three-Touch L to evoke Siri

**7 Play music**

Play music: Single touch to play music.  
Pause music: Single touch to pause music.  
Double touch R to next song  
Three touch R to Previous song

**Power bank battery status**

**Charging status:** the number of blue light flash time indicate battery status, the LED indicator will turn blue when the charging box is fully charged.  
**Power off status:** Press charging box key, LED indicator flash times indicate battery status.

Power: 0%- 25% blue light flash one time every 2 seconds,  
Power: 26%-50% blue light flash twice every 2 seconds,  
Power: 51%-75% blue light flash three times every 2 seconds,  
Power: 76%-100% blue light flash four times every 2 seconds.

**Specifications**

Items	Specifications
Headset	
Battery	Button cell 50mAh
Bluetooth Version	V5.0 + EDR/BLE
Working voltage	3.7 V-4.2V
Microphones sensitivity	105±3db
Bluetooth frequency band	2.4-2.48GHZ
Bluetooth range	10 M
Audio transmission protocols	A2DP/HFP/HSP/AVRCP
Power bank	
Capacity	300 mAh
DC output voltage	DC5V
DC output current(MAX)	1A
DC charging voltage	DC5V
DC charging current(MAX)	1A

**Notice**

1. The mobile can not find the headset if the "CGEB01WH/BK" is not paired. Please ensure the headset is in pairing model before you search it. (red and blue lights flashing alternately)  
2. If the headset can not find any pairing device for five minutes, it will power off automatically.

**Warm tips**

You must select a qualified adapter to charge this product. You must charge the bluetooth headset if it has not been used for more than 3 months.

**Warning**

1. Do not put the product at the environment of too low or too high temperature for a long time, that may cause deformation, reduce the battery capacity, even shorten service lifetime.  
2. Do not use the device when the thunderstorm coming, may cause a failure, and increase the risk of struck by lightning.  
3. Do not remove or modified headset for any reason, otherwise may lead to headset fault or burned, please send headset to authorized service center for repairs.  
4. Place the device and all accessories out of the reach of children and pets, small parts may be swallowed cause suffocation and serious consequences.  
5. Do not put the headset into the water.

**Troubleshooting**

Phenomenon	Reason	Solution
Starting-up failure	low battery	charge for the headset
No sound after paired	wrong paired	re-pairing
Red light shines during phone talking	low battery warning	please charge immediately
No indicator during charging	Headset didn't put into the charging cable well	check the headset if it's well put into
Shut down automatically	low battery	charge for the headset
Echo	volume is too high or environment is too noisy	adjust volume or change environment
Noise during phone calls	environment disturbance or headphone is too far away from device	change environment or shorten the distance between headphone and device
Low volume of the caller	wrong wear of headphone	adjust headphone position
Signal is not well, interrupting	environment disturbance or headphone is too far away from device	far away from the interference signal or shorten the distance between headphone and device

If you have any questions regarding our products, please visit us at [www.displays2go.com](http://www.displays2go.com) or contact D2G customer service at 844-221-3388.